



VGA & Audio to HDMI Converter

No.: 38165

Description

- Converts and combines VGA and analogue audio signals into an HDMI signal
- Perfect for using older VGA equipment with a HDMI display
- Supports resolutions up to 1080p
- Simple plug and play installation
- 2 year warranty

Please Note: This product is a format converter, from analogue to digital, there is no resolution scaling.

The VGA & Audio to HDMI Converter is capable of combining analogue video and stereo audio signals and converting them into a HDMI signal, perfect for using legacy PC and AV equipment seamlessly with the latest LCD, LED and Plasma displays.

The VGA and Audio converter features simple plug and play installation, there is no configuration required as there is no scaling of the video signal, with the output resolution matching the input resolution.

Technical details

Specification

- AV Interface: VGA to HDMI
- Interface Standard: HDMI 1.2a
- Supported Bandwidth: 6.75 Gbps
- Maximum Input Resolution: 1280x1024@75Hz Maximum Output Resolution: 1920x1080@60Hz
- HDCP Support: 1.1 Supported Audio: Audio Pass Through
- Separate Audio Ports: HDMI, RCA (Input)
- Special Features: -

Connectors

- Input: 1 x VGA (Female), 2 x RCA (female)
- Output: 1 x HDMI (Femále)
- Power: 5.5/2.1mm DC socket

- Dimensions WxDxH: 87x66x25mm (3.43x2.6x0.98in) Housing Material: Metal Net Weight: 0.246kg (0.54lb) Operating Temperature: 0°C 40°C (32°F 104°F) Storage Temperature: -20°C 60°C (-4°F 140°F) Humidity: 10 85% RH (non-condensing) Power Requirements: 5VDC 1A Colour: Black

Miscellaneous

- Packaging Type: Carton Box
 Packaging Dimensions: 170x120x60mm (6.69x4.72x2.36in)
 Gross Weight: 0.402kg (0.89lb)
 Warranty (Years): 2
 Certificated: CE, FCC, REACH & RoHS

Package Contents

- HDMI Converter
- Multi-Country Power Supply (EU, UK, US & AUS)
- Lindy Manual

Purchasing Information

- No.: 38165EAN: 4002888381659

© LINDY 2019