



USB to Parallel Converter MiniCN

No.: 42752

Description

- Connect a parallel printer to the computer's USB port
- 36 Way Mini Centronics Male to USB A Male connectors
- "Plug & Play" - USB bus-powered with no external power supply required
- Compatible with Windows computers
- 2 Year Warranty

This Lindy USB to Parallel Converter allows you to easily connect a parallel printer featuring a 36 Way Mini Centronics port to a computer's USB Type A port. It is also compatible with bi-directional printers.

The converter supports Plug and Play and as it is USB bus-powered, it can be installed quickly and simply with no need for additional power supplies.

Technical details

Specifications

- Interface: USB to Parallel
- Interface Standard: USB 1.1, IEEE1284
- Supported Bandwidth: 12Mbps, 150kbps
- Chipset: Prolific
- Compatibility: USB Type A equipped computers
- Power Delivery: -
- Special Features: -

Connectors

- Inputs: 1 x USB Type A (Male)
- Outputs: 1 x Mini-CN36 (Male)
- Power: Bus-powered

Physical Properties

- Dimensions WxDxH:
 - 39x32x11mm (1.54x1.26x0.43in)
 - 14x42x7mm (0.55x1.65x0.28in) / USB
- (Fixed) Cable Length: 2m (6.56ft)
- Housing Material: Plastic
- Net Weight: 0.06kg (0.13lb)
- Operating Temperature: 0°C - 60°C (32°F - 140°F)
- Storage Temperature: -20°C - 70°C (-4°F - 158°F)
- Humidity: -20°C - 70°C (-4°F - 158°F)

- Power Requirements: -
- Colour: Transparent anthracite

Miscellaneous

- Packaging Type: Polybag
- Packaging Dimensions: 310x210x10mm (12.2x8.27x0.39in)
- Gross Weight: 0.103kg (0.23lb)
- Warranty (Years): 2
- Certificated: CE, FCC, RoHS & REACH

Package Contents

- USB to Parallel Converter MiniCN
- Lindy Driver CD

Purchasing information

- No.: 42752
- EAN: 4002888427524

© LINDY 2019