



## USB 2.0 Fast Ethernet Converter

No.: 42948

### Description

- Connects a USB 2.0 computer with Micro-B interface to a Fast Ethernet network
- Supports 10BASE-T or 100BASE-TX, autosensing
- USB 2.0 data transfer rates up to 480Mbps, backwards compatible with USB 1.1 host controllers
- Bus-powered with no external power supply required
- 2 year warranty

The Lindy USB 2.0 Fast Ethernet Converter allows users to conveniently connect a notebook or tablet with USB Micro-B port to a Fast Ethernet network.

This converter is ideal for notebooks which do not feature wired network connectivity and for locations which lack wireless connectivity.

With its small size and lightweight design this USB 2.0 Fast Ethernet Converter is easy and convenient to carry, and because it is powered by the USB Bus no power adapter is required.

### Technical details

#### Specifications

- Interface: USB to RJ45
- Interface Standard: USB 2.0, 10/100 LAN
- Supported Bandwidth: 480Mbps, 10/100Mbps
- Chipset: AX88772B
- Compatibility: USB Type Micro-B equipped computers & mobile devices
- Power Delivery: -
- Special Features: -

#### Connectors

- Inputs: 1 x USB Type Micro-B (Male)
- Outputs: 1 x RJ45 (Female)
- Power: Bus-powered

#### Physical Properties

- Dimensions WxDxH: 20x67x14mm (0.79x2.64x0.55in)
- (Fixed) Cable Length: 80mm (3.15in)
- Housing Material: Plastic
- Net Weight: 0.016kg (0.04lb)
- Operating Temperature: 0°C - 40°C (0°F - 104°F)

- Storage Temperature: -20°C - 80°C (-4°F - 176°F)
- Humidity: 0 - 85% RH (non-condensing)
- Power Requirements: -
- Colour: Black

**Miscellaneous**

- Packaging Type: Polybag
- Packaging Dimensions: 120x140x20mm (4.72x5.51x0.79in)
- Gross Weight: 0.032kg (0.07lb)
- Warranty (Years): 2
- Certificated: CE, FCC, RoHS & REACH

**Package Contents**

- USB 2.0 Fast Ethernet Converter
- Driver CD
- Lindy Manual

**Purchasing information**

- No.: 42948
- EAN: 4002888429481